

PrimaVolt® No Minimum Load Dimmable Driver
Dimmer Compatibility Chart

BRAND	MODEL	INPUT	DIMMING RANGE	FORWARD/REVERSE PHASE
LUTRON®	SCL-153PR-WH	100-130V	0-100%	Forward Phase
	DVCL-153PR-WH	100-130V	0-100%	Forward Phase
	DVWCL-153PH-LA	100-130V	0-100%	Forward Phase
	CTCL-153PDH-LA	100-130V	0-100%	Forward Phase
	TGCL-153PR-WH	100-130V	0-100%	Forward Phase
	TGCL-153PH-WH	100-130V	0-100%	Forward Phase
	MACL-153MH-LA	100-130V	5-100%	Forward Phase
	CT-600PR-IV	100-130V	5-100%	Forward Phase
	CT-600PR-WH	100-130V	5-100%	Forward Phase
	CT-603PGH-WH	100-130V	9-100%	Forward Phase
	CT-103PR-WH	100-130V	8-100%	Forward Phase
	DV-600PR-BL	100-130V	5-100%	Forward Phase
	DV-600PR-WH	100-130V	4-100%	Forward Phase
	DVW-603PGH-WH	100-130V	4-100%	Forward Phase
	TG-600PR-LA	100-130V	8-100%	Forward Phase
	TG-600PR-IV	100-130V	8-100%	Forward Phase
	TG-600PR-WH	100-130V	8-100%	Forward Phase
	TG-10PR-WH	100-130V	15-100%	Forward Phase
	S-600PR-WH	100-130V	4-100%	Forward Phase
	MRF2-6ND-120-AL	100-130V	0-100%	Forward Phase
	MRF2-6CL-GR	100-130V	3-100%	Forward Phase
	DZ6HD	100-130V	23-100%	Forward Phase
	PD-6WCL	100-130V	25-100%	Forward Phase
	PD-5NE-WH	100-130V	22-100%	Forward Phase
	SELV-300P	100-130V	40-100%	Forward Phase
	MSCELV-600M	100-130V	12-100%	Forward Phase
	MEF2-6ELV-120	100-130V	12-100%	Reverse Phase
	DVELV-300P	100-130V	40-100%	Reverse Phase
	MRF2-6ND-120-AL	100-130V	0-100%	Reverse Phase
	MRF2-6CL-GR	100-130V	1-100%	Reverse Phase

**PrimaVolt® No Minimum Load Dimmable Driver
Dimmer Compatibility Chart**

BRAND	MODEL	INPUT	DIMMING RANGE	FORWARD/REVERSE PHASE
LEVITON	VPI06-1LZ	100-130V	15-100%	Forward Phase
	TTI06-1LZ	100-130V	1-100%	Forward Phase
	IPL06	100-130V	15-100%	Forward Phase
	6672	100-130V	15-100%	Forward Phase
	TBL03	100-130V	12-100%	Forward Phase
	6602	100-130V	10-100%	Forward Phase
	6683	100-130V	12-100%	Forward Phase