



Hanging Brackets (optional) - 1 bracket w/screws



AL-50-19-9971-WH

AL-50-19-9971-ALP



1. Before installing the tape light in the channel, test the connection to power by attaching the appropriate connector to the tape light and then connecting to DC power.
2. Channel end caps are available in open and closed models. The open end cap lets the power wire pass from the inside of the channel to the DC power supply. *Please note: you may need to remove the white jacket around the wires of the Tape Light Splice Connector so the wires can fit through the opening in the end cap.* On the other end of the channel, the closed end cap provides a seal. Be sure to insert the power wire through the open end cap before attaching to the DC power supply.
3. When all connections are secure, and before permanently installing the tape light in the channel, be sure to account for the space to be taken up by the connector in the channel, measuring so that the end caps can fit in the channel once tape and connector are installed.
4. Insert the tape light into the channel by peeling off the covering of the tape light's adhesive backing and pressing the tape in a straight line, starting at one end of the channel and moving to the other end to ensure flat, even adhesion.
5. Insert the end caps into the ends of the channel with even pressure on both sides to ensure a snug fit. Secure the end caps with the included screws.
6. Put the cover in place by squeezing the sides and pressing the cover down into the grooves at the top of the channel, starting at one end and moving to the other.
7. Use a tape measure to determine height and placement of the mounting rings (A). Mark the screw positions.
8. Inside the mounting ring position on the end nearest to DC power, drill a hole large enough to accommodate the power wire.
9. If using hanging brackets (optional), position the brackets on the closet bar.
10. Slip the mounting rings onto the ends of the bar.
11. Connect and run DC power wire into the wall.
12. Attach the bar to the wall using screws and the mounting rings in the premarked positions.