

## PrimaVolt® Dimmable Driver Dimmer Compatibility Chart

BRAND	MODEL	INPUT	DIMMING RANGE	FORWARD/REVERSE PHASE
<b>LUTRON®</b>	SCL-153PR-WH	100-130V	2-100%	Forward Phase
	DVCL-153PR-WH	100-130V	2-100%	Forward Phase
	DVWCL-153PH-LA	100-130V	2-100%	Forward Phase
	CTCL-153PDH-LA	100-130V	2-100%	Forward Phase
	TGCL-153PR-WH	100-130V	2-100%	Forward Phase
	TGCL-153PH-WH	100-130V	2-100%	Forward Phase
	MACL-153MH-LA	100-130V	10-100%	Forward Phase
	CT-600PR-IV	100-130V	20-100%	Forward Phase
	CT-600PR-WH	100-130V	20-100%	Forward Phase
	CT-603PGH-WH	100-130V	30-100%	Forward Phase
	CT-103PR-WH	100-130V	28-100%	Forward Phase
	DV-600PR-BL	100-130V	20-100%	Forward Phase
	DV-600PR-WH	100-130V	16-100%	Forward Phase
	DVW-603PGH-WH	100-130V	20-100%	Forward Phase
	TG-600PR-LA	100-130V	30-100%	Forward Phase
	TG-600PR-IV	100-130V	30-100%	Forward Phase
	TG-600PR-WH	100-130V	30-100%	Forward Phase
	TG-10PR-WH	100-130V	40-100%	Forward Phase
	S-600PR-WH	100-130V	17-100%	Forward Phase

<b>LEVITON</b>	VPI06-1LZ	100-130V	27-100%	Forward Phase
	6672	100-130V	35-100%	Forward Phase
	TBL03	100-130V	30-100%	Forward Phase
	6683	100-130V	40-100%	Forward Phase