

ALLOY LED Specifications

Casambi Compatible Wireless 4-Button Dimmer Wall Switch

AL-60-04-0007



The Casambi compatible wireless switches provide automatic lighting control for a variety of indoor applications. They can replace any standard single-pole wall switch. Alloy LED offers wall switches for any application you may need.

This Wireless 4-Button Dimmer Switch's buttons can be used for on/off, dimming, scenes, and color turning controls. The configurations of each button can also be personalized.

- Bluetooth SIG mesh
- Manual on/off (wireless)
- Dim up/down (wireless)
- LED status indicator light
- 4-Button may be personalized
- Mounts in any standard wall box

For wiring, see specification sheet of desired Casambi module.

TECHNICAL INFORMATION

Input Voltage	120-277V AC, 50/60Hz
Power Consumption	1.5W maximum
Maximum Bluetooth Range	30 ft.
Mounting	Standard wall box
Scenes	Up to 255 scenes in the app
Certifications	UL Listed
Warranty	5 years



PRODUCT INFORMATION

Item Number	Description
AL-60-04-0007	Casambi Compatible Wireless 4-Button Dimmer Wall Switch

DIMENSIONS

