

ALLOY LED Specifications

Casambi Compatible Wireless Dual Rocker Batteryless Wall Switch

AL-60-04-0005



The Casambi compatible wireless switches provide automatic lighting control for a variety of indoor applications. Alloy LED offers wall switches for multiple application needs.

This self-powered dual rocker wall switch comes with a micro-generator-powered Bluetooth BLE Transmitter that sends a wireless signal, eliminating the need for wires or batteries. They can be surface- or flush-mounted and offers manual on/off and app-controlled dimming.

This wall switch requires dual-channel controller. It is not Casambi CBU-TED compatible.

TECHNICAL INFORMATION

Maximum Bluetooth Range	30 ft.
Frequency	Bluetooth (BLE) (2.4Ghz)
Power	Self-generated when switch is pressed
Rockers	2 Rockers
Wall Plate Dimensions	2.75 x 4.5 x 0.62 in.
Zone	2 zones
Warranty	5 years

PRODUCT INFORMATION

Item Number	Description
AL-60-04-0005	Dual Rocker Casambi Compatible Wireless Batteryless Wall Switch

DIMENSIONS

